# Canon LENS TECHNICAL REPORT

VOL.4

CANON INC.
LENS PRODUCTS DEVELOPMENT CENTER

This Technical Report describes the new closeup accessories designed for the EOS cameras. With the current boom in nature photography, more users want to photograph flowers, insects, and other nature subjects at high magnifications. Although a macro lens is most ideal for closeup photography, a simple accessory enabling convenient closeup photography would attract more users into this field.

Based upon this premise, Canon has developed closeup lenses 500, 250D, and 500D and extension tube EF12 to make the closeup system for EOS cameras more complete.

# Convenient Closeup Accessories

Closeup Lenses 500, 250Dand 500D and Extension Tube EF12





Photo 2: Extension tube EF12

Photo 1: From the left, closeup lenses 250D (58mm dia.), 500D (77mm dia.), and 500 (77mm dia.)

#### Closeup lenses 500, 250D, and 500D

These closeup lenses are screwed on to the front of an EF lens just like a filter. Closeup lens 500 is geared for newcomers to closeup photography, while closeup lenses 250D and 500D are for users who want higher image quality.

For the FD lenses, closeup lenses 500T (dedicated to the FD80-200mm f/4L lens), 240, and 450 are already available. Now for the EF lenses, the low-cost closeup lens 500 and top-notch closeup lenses 250D and 500D are available. The 500 and 500D come in four sizes (52, 58, 72, and 77 mm) and the 250D come in two sizes (52 and 58 mm).

All the closeup lenses have super spectra coatings to prevent shifts in the color balance of the prime lens.

#### ●Extension tube EF12

Extension tube EF12 is installed between the EF lens and the camera body, thereby enabling closeup photography. Almost all EF lenses can be attached to the EF12. Being 12 mm long, it is about half the length of extension tube EF25. The EF25 and EF12 offer a wide magnification range for closeup photography.

# Closeup Lens and Extension Tube Principles

Closeup photography accessories include macro lenses, bellows, and macro photo lenses. Just by attaching a closeup lens or an extension tube to an EF lens, closeup photography can be enjoyed in the same way as with a macro lens.o Closeup lens principle


When the prime lens is focused at infinity, the incident light rays become parallel. The light rays from the

Fig. 1 Light rays passing through a closeup lens.

Object focal point

Fig. 2 EF 50mm f/1.4 USM lens with closeup lens 250D attached.

Focal length



When the prime lens is focused at infinity, the closeup lens' object point is where sharp focus is achieved. (In the above figures, the light rays are not drawn to scale.)

errations will become more pronounced. To minimize aberrations, lenses with a focal length ranging from 50mm to 135mm are recommended as the prime lens for closeup lens 250D. For closeup lenses 500 and 500D, prime lenses with a focal length ranging from 70mm to 350mm are recommended. Sample combinations are shown as follows:

- •EF 50mm f/1.4 USM lens with closeup lens 250D, 500, or 500D.
- •EF 70-210mm f/3.5-4.5 USM zoom lens with closeup lens 500 or 500D.

Also, with a fixed-length zoom lens such as the EF 70-200mm f/2.8L USM as the prime lens, the image magnification can be changed by zooming while maintaining the same point of focus.

#### **Extension tube EF12**

This extension tube extends the distance between the lens and film. The shorter the focal length of the lens, the higher the image magnification will be. In effect, the working distance\* (between the front of the lens and the subject) becomes shorter. Also, if a zoom lens is used, a zooming operation will change the image magnification and point of focus at the same time. Therefore, it is easier to use the extension tube with a single focal length lens. \*To be described later.

closeup lens' object point passing through the closeup lens also become parallel. Therefore, by attaching a converging closeup lens to the front of a prime lens, closeup photography is enabled. (The "250" and "500" designations of the closeup lenses refer to the focal length [mm] shown in the figure.) Also, when the prime lens is focused at its minimum focusing distance, a higher magnification is achieved.

#### Extension tube principle

Extension tube EF12 is a fixed-length tube equipped with a lens mount and electrical contacts. It has no lenses. When the tube is installed between the camera and lens, the lens' is extended according to the tube's length. The minimum focusing distance is thereby shortened, resulting in a higher magnification. Also, the shorter the focal length of the lens, the higher the magnification will be when it is attached to an extension tube. In the case of the EF 35mm f/2 lens, its maximum magnification will increase from 0.23X to 0.58X when the EF12 is attached. See Photos 3 and 4.

#### Selecting a Prime Lens

For closeup lenses 500, 250D, and 500D Prime lenses are designed to minimize inherent aberrations. If a supplementary lens such as a closeup lens is attached to a prime lens, the ab-




Photo 3: Taken at the minimum focusing distance with the EF 35mm f/2 lens. (0.23X magnification)



Photo 4: Taken at the minimum focusing distance with the EF 35mm f/2 lens attached to extension tube EF12. (0.58X magnification)

## For Better Results

The closeup lenses and extension tube can be easily attached to an EF lens. The picture-taking operation is identical to when an EF lens is used alone. Understanding the closeup accessory's possibilities will result in better closeup photographs. A few closeup picture-taking hints are described below.

#### Using the maximum magnification

To attain maximum magnification, turn the prime lens' focusing ring to the minimum focusing distance. To focus the subject, move the camera forward or back. For an intermediate magnification, set the prime lens' focusing ring to a longer focusing distance. To focus the subject, move the camera forward or back. If you try to focus the subject by adjusting the distance between the prime lens and film plane, the magnification will also change, making it difficult to compose the shot. Using a sturdy tripod with a focusing stage allowing the camera to move forward or back is recommended.

# Extension tubes effective with super telephoto lenses

Since the super telephoto L lenses have a large front element, closeup lenses are too small to be attached. An extension tube is therefore used for closeup photography with such lenses. Although super telephoto EF lenses are often used for portraiture, their maximum magnification is low. (The EF 200mm f/1.8 USM and EF 300mm f/2.8L USM lenses have a magnification of 0.09X and 0.11X respectively.) At such magnifications, the angle of view permits head-andshoulders shots at most in portraiture. However, when extension tube EF12 is attached to increase the magnification, the face can fill the entire frame. For example, with the extension tube EF12 attached to the EF 300mm f/2.8L USM lens, the maximum magnification is increased from 0.11X to 0.21X. See Photos 5 and 6.

#### Working distance

An adequate working distance (distance between the subject and the front of the lens) is required for photographing insects which may fly or run away when



#### 0.15x

- •EF 400mm f/5.6 USM + Extension tube EF12
- •EF 100-300mm f/4.5-5.6 USM + Extension tube EF12



#### 0.25x

- •EF 85mm f/1.8 USM + Extension tube EF12
- •EF 70-210mm f/3.5-4.5 USM + Extension tube EF12



#### 1.5x

- •EF 50mm f/2.5 compact macro lens
- •EF 80-200mm f/2.8L +Closeup lens 500/500D



#### 0.75x

- •EF 50mm f/2.5 compact macro + Extension tube EF12
- •EF 75-300mm f/4-5.6 USM + Closeup lens 500/500D



#### LOx

- •EF 100mm f/2.8 macro
- •EF 80-200mm f/4.5-5.6 USM + Closeup lens 250D

tographing insects which may fly or run away when approached or when artificial light must be used. The prime lens and closeup accessory must be properly matched to allow an adequate working distance when you cannot get very close to the subject. With closeup lenses 250D and 500/500D, the working distance is 0.25 m and 0.5 m respectively. With the extension tube attached to a telephoto lens, the working distance can be 0.5 m or longer.

### Working distances with the extension tube EF12 attached:

- •EF 100mm f/2 USM: Approx. 0.4 m to 0.8 m
- •EF 135mm f/2.8:
- Approx. 0.7 m to 1.6 m
- •EF 35-105mm f/4.5-5.6
- Approx. 0.4 m to 1 m
- •EF 70-210mm f/3.5-4.5 USM:
- Approx. 0.3 m to 3.6 m



Photo 5: Taken with the EF 300mm f/2.8L USM lens (Min. focusing distance of 3m and magnification of 0.11X.)



Photo 6: Taken with the EF 300mm f/2.8L USM lens attached to the EF12. (Min. focusing distance of 1.9m and magnification of 0.21X.)

#### Stop Down for Better Image Quality

When a closeup lens or extension tube is attached, aberrations will increase. As a corrective measure, stop down the aperture to obtain high-resolution, and high-contrast photographs. To improve image quality, an aperture of f/5.6 to f/8 is recommended. (For an explanation of how stopping down the aperture corrects aberrations, see Technical Report Vol. 3.)

Closeup lenses 250D and 500D consist of two elements: a converging lens element and diverging lens element. Such "color-canceling elements" serve to correct chromatic aberrations. Thus, these two closeup lenses are recommended for users who want high image quality in their closeup photos. (For an explanation of how chromatic aberrations affect the image quality, see Technical Report Vol. 3.)



Photo 7: Image taken at maximum aperture with closeup lens 250D attached to the EF 50mm f/1.4USM lens.



Photo 8: Image taken at f/8 with closeup lens 250D attached to the EF 50mm f/1.4 USM lens.

#### Q & A

#### On closeup lenses

- Q1: How about stacking two or more closeup lenses on a prime lens?
- A1: This is not recommended since it may degrade the image quality and cause vignetting with certain prime lenses.
- Q2: Can a filter be attached to the front of the closeup lens?
- A2: Attaching one filter is okay.
- Q3: Are there any lenses which are not compatible with a closeup lens?
- A3: Refer to the table on the right.
- Q4: Is any exposure compensation necessary for TTL metering?
- A4: No. Autoexposure can be used as usual.
- Q5: Will the exposure reading be correct in all the metering modes?
- A5: Yes.
- Q6: Is autofocusing possible?
- A6: With certain lenses, proper autofocusing cannot be done. In such cases, focus manually.

Incompatible Lenses	Reason		
EF20mm f/2.8 USM	Vignetting will occur at infinity		
TS-E24mm f/3.5L			
TS-E45mm f/2.8	Vignetting will occur when the lens is tilted or shifted.		
TS-E90mm f/2.8	iens is thed of shined.		
EF20-35mm f/2.8L			
EF20-35mm f/3.5-4.5 USM			
EF28-70mm f/2.8L USM	Vignetting will occur at the		
EF28-80mm f/3.5-5.6II USM	wide angles.		
EF28-105mm f/4.5-5.6 USM			
EF35-350mm f/3.5-5.6L USM			
EF14mm f/2.8L USM			
EF15mm f/2.8FE	100.00		
EF200mm f/1.8L USM			
EF300mm f/2.8L USM	Unattachable to the front of		
EF400mm f/2.8L USM	these lenses.		
EF500mm f/4.5L USM			
EF600mm f/4L USM			
EF1200mm f/5.6L USM	;   1		

#### On extension tube EF12

- Q1: How about connecting two or more extension tubes in tandem?
- A1: This is not recommended since it may degrade the image quality and cause vignetting with certain lenses.
- Q2: Is any exposure compensation necessary for TTL metering?
- A2: If the EF 50mm f/1.4 USM, EF 50mm f/1.8II, or EF 85mm f/1.2L USM is used as the prime lens and the camera is an EOS-5 attached to extension tube EF12, set the exposure compensation on the camera to +1/2 stop.
- Q3: Are there any lenses which are not compatible with the extension tube?
- A3: If the extension tube is attached to the EF 14mm f/2.8L USM lens or EF 15mm f/2.8 fisheye lens, the point of focus will be within the optical system or near the front of the lens. Also, attaching the extension tube to the EF 50mm f/1.0L USM lens will cause vignetting. Thus, the EF12 should not be attached to these lenses. Also note that vignetting may occur with TS-E lenses when they are shifted.
- Q4: Will the exposure reading be correct in all the metering modes?
- A4: In the case of spotmetering, the correct exposure reading will not be obtained.

# Supplement: Extension Tube EF25

For your reference, information on the existing extension tube EF25 is presented here.

#### **Application**

As with the extension tube EF12, the extension tube EF25 is attached to a prime lens and mounted on a camera. The maximum magnification and focusing are achieved in the same way as with the extension tube EF12.

#### **Cautionary Notes**

Basically the same as for the extension tube EF12. To improve image quality, stop down the prime lens to f/5.6 to f/8.

#### Extension tube EF25 Q & A

- Q1: How about connecting two or more extension tubes in tandem?
- A1: This is not recommended since it may degrade the image quality and cause vignetting with certain lenses.
- Q2: Is any exposure compensation necessary for TTL metering?
- A2: Refer to the adjacent table. The lenses listed require the exposure compensation (on the camera) indicated.
- Q3: Are there any lenses which are not compatible with the extension tube?




Photo 9: Extension tube EF25

\$4000000000000000000000000000000000000	Exposure co	mpensation	
Compensatable lenses	(EV)		
	EOS-1N	EOS-5	
EF50mm f/1.4 USM	0	+1/2	
EF50mm f/1.8 II	0	+1/2	
EF85mm f/1.2L USM	+1	+1	

Incompatible Lenses	Reason				
EF14mm f/2.8L USM					
EF15mm f/2.8 FE	The point of focus will fall within the optical system.				
EF20mm f/2.8 USM					
EF50mm f/1.0L USM	Vignetting will occur.				
TS-E45mm f/2.8	Image degradation will be substantial.				
TS-E24mm f/3.5L	V6				
TS-E90mm f/2.8	Vignetting will occur when the lens is shifted.				
EF20-35mm f/2.8L	At wide angles, the point of focus will be within the optical system. (Zoom lenses				
EF20-35mm f/3.5-4.5 USM	with other focal length ranges can be used.)				

A3: Refer to the table below.

Q4: Will the exposure reading be correct in all the metering modes?

A4: In the case of spotmetering, the correct exposure reading will not be obtained.

### Dimensions and WeightCloseup Lenses 500, 250D, and 500D/Extension Tube EF25

Lens	Size	52	58	72	77
	Max. Diameter	φ 54	φ 60	φ75	φ 80
	mm(inch)	( \$2-1/8)	( ¢ 2-3/8)	( ø 2-15/16)	( φ 3-1/8)
500	Length (mm)	5.7	6.8	7.3	8.3
500	mm (inch)	(3/16)	(1/4)	(5/16)	(3/8)
	Weight	16	24	43	44
	g (onz)	(0.6)	(0.8)	(1.5)	(1.5)
	Max. Diameter	φ 54	φ 60		
	mm(inch)	( \$2-1/8)	( \phi 2-3/8)		
oron	Length (mm)	10.2	12		
250D	mm (inch)	(3/8)	(7/16)		
	Weight	55	80		
	g (onz)	(1.9)	(2.8)		
	Max. Diameter	¢ 54	φ 60	φ75	ø 80
	mm (inch)	( ¢ 2-1/8)	· ( \$\phi 2-3/8)	( \$\phi 2-15/16)	( φ 3-1/8)
E00D	Length (mm)	9.8	10.5	12.7	13.5
500D	mm (inch)	(3/8)	(3/8)	(1/2)	(9/16)
	Weight	40	60	120	145
	g (onz)	(1.4)	(2.1)	(4.2)	(5.1)

Extension T	ube EF12
Max. Diameter	φ 66.5
mm(inch)	( φ 2-5/8)
Length	12.3
mm(inch)	(1/2)
Weight	66
g (onz)	(2.3)

Extension Tube EF25						
φ 67.6						
( φ 2-11/16)						
27.3						
(1-1/16)						
125						
(4.4)						

# Closeup Lenses 500, 250D, and 500D, magnification

Long	Close-up lenses 2500		Close-up lenses 500/500D		
Lens	Size	Magnification (X)	Magnification (X)		
EF14mm f/2.8L USM	Not Available				
Fish-eye 15mm f/2.8	Not Available				
EF20mm f/2.8 USM	72	***************************************	0.17~0.04		
EF24mm f/2.8	58	0.25~0.10	0.20~0.05		
EF28mm f/2.8	52	0.24~0.12	0.19~0.06		
EF35mm f/2	52	0.36~0.14	0.30~0.07		
EF50mm f/1.0L USM	72	Mahala	0.24~0.10		
EF50mm f/1.4 USM	58	0.35~0.21	0.25~0.10		
EF50mm f/1.8II	52	0.36~0.20	0.25~0.10		
EF50mm f/2.5 Compact-macro	52	0.68~0.20	0.59~0.10		
EF85mm f/1.2L USM	72	pana	0.28~0.17		
EF85mm f/1.8 USM	58	0.50~0.34	0.31~0.17		
EF100mm f/2 USM	58	0.57~0.40	0.35~0.20		
EF100mm f/2.8 Macro	52	1.41~0.41	1.21~0.20		
EF135mm f/2.8	52 0.70~0.55		0.41~0.27		
EF200mm f/1.8L USM		Not Available			
EF200mm f/2.8L USM	72	Marina	0.57~0.39		
EF300mm f/2.8L USM		Not Available			
EF300mm f/4L USM	77	Acceptan	0.70~0.59		
EF400mm f/2.8L USM		Not Available			
EF400mm f/5.6L USM	77	annea .	0.91~0.78		
EF500mm f/4.5L USM		Not Available			
EF600mm f/4L USM	Not Available				
EF1200mm f/5.6L USM		Not Available			
TS-E24mm f/3.5L	72	Manufacture .	0.19~0.05		
TS-E45mm f/2.8	72	MARKET .	0.25~0.09		
TS-E90mm f/2.8	58	0.69~0.36	0.49~0.18		

		Close-up le	Close-up lenses 250D Magnification (X)		ses 500/500D
Lens	Size	Magnific			Magnification (X)
		WIDE	TELE	WIDE	TELE
EF20-35mm f/2.8L	72	-		Vignetting	0.15~0.07
EF20-35mm f/3.5-4.5 USM	77			Vignetting	0.19~0.07
EF28-70mm f/2.8L USM	77		NAME OF THE OWNER OWNER OF THE OWNER OWNE	Vignetting	0.30~0.14
EF28-80mm f/3.5-5.6II USM	58	Vignetting	0.51~0.31	Vignetting	0.38~0.15
EF28-105mm f/3.5-4.5 USM	58	Vignetting	0.43~0.41	Vignetting	0.30~0.20
EF35-80mm f/4-5.6III	52	0.23~0.15	0.49~0.31	0.17~0.07	0.36~0.15
EF35-80mm f/4-5.6 USM	52	0.24~0.15	0.50~0.31	0.18~0.07	0.37~0.15
EF35-105mm f/4.5-5.6 USM	58	0.21~0.15	0.60~0.41	0.13~0.07	0.37~0.20
EF35-135mm f/4.5-5.6USM	58	0.18~0.15	0.54~0.50	0.12~0.07	0.32~0.26
EF35-350mm f/3.5-5.6L USM	72		none of the second	Vignetting	0.70~0.68
EF70-200mm f/2.8L USM	77			0.21~0.14	0.55~0.39
EF70-210mm f/3.5-4.5 USM	58	0.34~0.29	0.85~0.83	0.20~0.14	0.51~0.41
EF75-300mm f/4-5.6II USM	58	0.41~0.32	1.54~1.18	0.23~0.15	0.89~0.58
EF80-200mm f/4.5-5.6II	52	0.43~0.34	0.99~0.78	0.24~0.17	0.57~0.38
EF100-300mm f/5.6L	58	0.55~0.41	1.59~1.20	0.31~0.20	0.92~0.59
EF100-300mm f/4.5-5.6 USM	58	0.48~0.42	1.22~1.19	0.28~0.21	0.70~0.58

Extension Tube EF12, magnification, focusing distance ranges and working distance ranges

Lens	Magnification	Focusing distance ranges	Woking distance ranges			
Lens	(X)	mm (inch)	mm (inch)			
EF14mm f/2.8L USM		Not Available				
Fish-eye 15mm f/2.8	0.94~0.80	112~119 (4-11/16~4-7/16)	2~5 (1/16~3/16)			
EF20mm f/2.8 USM	0.72~0.60	138~141 (5-7/16~5-9/16)	12~16 (1/2~5/8)			
EF24mm f/2.8	0.64~0.50	138~142 (5-7/16~5-9/16)	34~39 (1-5/16~1-9/16)			
EF28mm f/2.8	0.56~0.43	147~159 (5-13/16~6-1/4)	46~62 (1-13/16~2-7/16)			
EF35mm f/2	0.58~0.35	169~201 (6-5/8~7-15/16)	63~104 (2-1/2~4-1/16)			
EF50mm f/1.0L USM		Not Available				
EF50mm f/1.4 USM	0.39~0.24	247~323 (9-3/4~12-11/16)	142~226 (5-9/16~8-7/8)			
EF50mm f/1.8II	0.39~0.24	249~324 (9-13/16~12-3/4)	156~239 (6-1/8~9-7/16)			
EF50mm f/2.5 Compact-macro	0.74~0.24	208~321 (8-3/16~12-5/8)	92~230 (3-5/8~9-1/16)			
EF85mm f/1,2L USM	0.25~0.15	497~699 (19-9/16~27-1/2)	346~560 (13-5/8~22-1/16)			
EF85mm f/1.8 USM	0.27~0.15	498~723 (19-5/8~28-11/16)	375~605 (14-3/4~23-13/16)			
EF100mm f/2 USM	0.27~0.13	573~956 (22-9/16~37-5/8)	445~829 (17-1/2~32-5/8)			
EF100mm f/2.8 Macro	1.17~0.12	309~1024 (12-3/16~40-5/16)	134~896 (5-5/16)			
EF135mm f/2.8	0.22~0.09	862~1735 (33-15/16~68-5/16)	715~1588 (28-3/16~62-1/2)			
EF200mm f/1.8L USM	0.15~0.06	1585~3353 (62-3/8~132-1/16)	1336~3104 (52-5/8~122-3/16)			
EF200mm f/2.8L USM	0.23~0.06	1169~3482 (46-1/16~137-1/16)	978~3291 (38-1/2~129-9/16)			
EF300mm f/2.8L USM	0.16~0.04	2324~7607 (91-1/2~299-1/2)	2038~7322 (80-1/4~288-1/4)			
EF300mm f/4L USM	0.18~0.04	1986~7786 (78-3/16~306-9/16)	1726~7526 (67-15/16~296-5/16)			
EF400mm f/2.8L USM	0.15~0.03	3293~13837 (129-5/8~544-3/4)	2914~13457 (114-3/4~529-13/16)			
EF400mm f/5.6L USM	0.16~0.03	2893~13449 (113-7/8~529-1/2)	2583~13138 (101-11/16~517-1/4)			
EF500mm f/4.5L USM	0.14~0.03	4199~21363 (165-5/16~841-1/16)	3768~20932 (148-3/8~824-1/8)			
EF600mm f/4L USM	0.13~0.02	5111~29571 (201-1/4~1164-3/16)	4627~29087 (182-3/16~1145-3/16)			
EF1200mm f/5.6L USM	0.12~0.01	10974~113572 (432-1/16~4471-5/16)	10139~112740 (399-3/16~4438-9/16)			
TS-E24mm f/3.5L	0.62~0.49	171~179 (6-3/4~7-1/16)	29~37 (1-3/16~1-7/16)			
TS-E45mm f/2.8	0.44~0.27	239~299 (9-7/16~11-3/4)	94~153 (3-11/16~6-1/16)			
TS-E90mm f/2.8	0.43~0.14	415~817 (16-5/16~32-3/16)	264~691 (10-3/8~27-3/16)			

	Magni	fication	Focusing dis	stance ranges	Working dist	ance ranges
Lens	(X)		mm	mm (inch)		(inch)
	WIDE	TELE	WIDE	TELE	WIDE	TELE
EF20-35mm f/2.8L	0.66-0.60	0.46~0.36	157~161	201~226	13~17	63~87
EF20-33HIII 1/2.6L	0.00~0.00	0.46~0.36	(6-3/16~6-3/8)	(7-15/16~8-7/8)	(1/2~-11/16)	(2-1/2~3-7/16)
EF20-35mm f/3.5-4.5 USM	0.70~.0.60	0.53~0.36	135~141	177~212	11~17	53~89
LI 20-03/IIII 1/3.3-4.3 USM	0.70 ~ 0.60	0.55*~0.56	(5-5/16~5-9/16)	(6-15/16~8-3/8)	(7/16~11/16)	(2-1/16~3-1/2)
EF28-70mm f/2.8L USM	0.500.40	0.39~0.18	222~235	336~566	28~41	165~394
L1 20-70/11/11 1/2.0L 03/VI	0.52~0:42	0.39~0.16	(8-3/4~9-1/4)	(13-1/4~22-5/16)	(1-1/8~1/5/8)	(6-1/2~15-1/2)
EF28-80mm f/3.5-5.6II USM	0.570.40	0.47~0.16	172~192	291~664	33~60	152~532
LI 20-00HHI 1/3.3-3.0H USW	0.37~0.42	0.47~0.16	(6-3/4~7-9/16)	(11-7/16~26-1/8)	(1-5/16~2-3/8)	(6~20-15/16)
EF28-105mm f/3.5-4.5 USM	0.53~0.42	0.00. 0.10	166~183	322~1033	36~54	165~876
EF26-10311111 1/3.5-4.5 USW	0.53~0.42	0.36~0.12	(6-9/16~-7-3/16)	(12-11/16~40-11/16)	(1-7/16~2-1/8)	(6-1/2~34-1/2)
EF35-80mm f/4-5.6III	0.50 0.04	0.44~0.16	183~225	292~668	58~92	166~534
EF35-60/IIII I/4-5.6III	0.50~0.34	0.44~0.16	(7-3/16~8-7/8)	(11-1/2~26-5/16)	(2-5/16~3-5/8)	(6-9/16~21-1/16)
EF35-80mm f/4-5.6 USM	0.51.004	0.46~0.16	182~226	285~669	56~106	158~550
EF35-80IIIII 1/4-5.6 USW	0.51~0.34		(7-3/16~8-7/8)	(11-1/4~26-5/16)	(2-3/16~4-3/16)	(6-1/4~21-5/8)
EF35-105mm [/4,5-5,6 USM	0.00~.0.04	34 0.28~0.12	221~225	580~1080	100~103	439~945
C1 33* 1031/111 //4,3*3.0 03W	0.367~0.34		(8-11/16~8-7/8)	(22-13/16~42-1/2)	(3-15/16~4-1/16)	(17-5/16~37-3/16)
EF35-135mm f/4.5-5.6USM	0.400.04	0.29~0.10	208~234	478~1675	67~93	311~1509
EF35-135HHH #4.5-5.6USM	. 0.42~0.34	0.29~0.10	(8-3/16~-9-3/16)	(18-13/16~65-15/16)	(2-5/8~-3-11/16)	(12-1/4~-59-7/16)
EF35-350mm f/3.5-5.6L USM	0.49~.0.94	0.40 0.04	268~294	1779~10146	46~72	1482~9849
E1 33-330(I)((1/3.3-3.8E 03)()	0.45.~0.54	0.19/~0.04	(10-9/16~11-9/16)	(70-1/16~399-7/16)	(1-13/16~2-13/16)	(58-3/8~387-3/4)
EF70-200mm f/2.8L USM	: 0.00±.0.47	0.22~0.06	553~622	1161~3392	306~375	914~3145
LI 70-20011111 1/2.8L USW	0.22~0.17	0.22~0.06	(21-3/4~24-1/2)	(45-11/16~133-9/16)	(12-1/16~14-3/4)	(36~123-13/16)
EF70-210mm (/3.5-4.5 USM	0.05-0.47	0.25~0.06	467~615	929~3841	293~441	707~3619
EF70-210IHIII 1/3.5-4.5 USM	0.25~0.17	0.25~0.06	(18-3/8~24-3/16)	: (36-9/16~151-1/4)	(11-9/16~17-3/8)	(27-13/16~142-1/2)
EETE OOOMAN HA E OU LICH	0.01 0.10	004 004	611~699	1357~7694	421~522	. 1112~7461
EF75-300mm f/4-5.6II USM	0.21~0.16	0.31~0.04	(24-1/16~-27-1/2)	(54-1/8~-302-15/16)	(16-9/16 20-9/16)	(43-13/16293-3/4)
EF80-200mm f/4.5-5.6ll	0.04 0.45	0.00 0.00	619~774	1172~3523	482~645	997~3355
EF80-200mm (/4.5-5.6)	0.21~0.15	0.23~0.06	(24-3/8~30-1/2)	(46-1/8~138-11/16)	(19~25-3/8)	(39-1/4~132-1/8)
EE100 200mm #E 61	0.04 - 0.40	0.00- 0.04	823~1105	1368~7845	585~883	1102~7596
EF100-300mm f/5.6L	0.21~0.12	0.32~0.04	(32-3/8~43-1/2)	(53-7/8~308-7/8)	(23-1/16~34-3/4)	(43-3/8~298-15/16)
EE100 200 PM U4 E E 0 U014	0.01 - 0.10		720~1140	1278~7847	546~959	1055~7624
EF100-300mm I/4.5-5.6 USM	0.21~0.12	0.26~0.04	(28-3/8~44-7/8)	(50-5/16~308-15/16)	(21-1/2~37-3/4)	(41-9/16~300-3/16)

# Extension Tube EF25, magnification, focusing distance ranges and working distance ranges

Lens	Magnification Focusing distance ranges		Working distance ranges			
Lens	(X)	mm (inch)	mm (inch)			
EF14mm f/2.8L USM		Not Available				
Fish-eye 15mm f/2.8	Not Available					
EF20mm f/2.8 USM		Not Available				
EF24mm f/2.8	1.22~1.11	131~133 (5-1/8~5-1/4)	12~15 (1/2~9/16)			
EF28mm f/2.8	1.09~0.95	137.7~137.9 (5-7/16~5-7/16)	22~25 (7/8~1)			
EF35mm f/2	1.00~0.77	158~160 (6-1/4~6-5/16)	37~48 (1-1/2~1-7/8)			
EF50mm f/1.0L USM		Not Available				
EF50mm f/1.4 USM	0.68~0.53	200~220 (7-7/8~8-11/16)	82~110 (3-1/4~4-5/16)			
EF50mm f/1.8II	0.68~0.53	207~221 (8-1/8~8-11/16)	99~120 (3-7/8~4-3/4)			
EF50mm f/2.5 Compact-macro	1.04~0.54	203~223 (8~8-3/4)	72~117 (2-13/16~4-5/8)			
EF85mm f/1.2L USM	0.42~0.33	369~409 (14-1/2~16)	203~253 (8~10)			
EF85mm f/1.8 USM	0.44~0.32	386~428 (15-3/16~16-7/8)	249~291 (9-13/16~11-1/2)			
EF100mm f/2 USM	0.42~0.28	425~543 (16-3/4~21-3/8)	309~401 (12-3/16~15-13/16)			
EF100mm f/2.8 Macro	1.38~0.27	314~593 (12-3/8~23-3/8)	101~426 (4~16-3/4)			
EF135mm f/2.8	0.33~0.20	675~938 (26-9/16~36-15/16)	514~776 (20-1/4~30-9/16)			
EF200mm f/1.8L USM	0.23~0.14	1167~1673 (45-15/16~65-7/8)	903~1409 (35-9/16~55-1/2)			
EF200mm f/2.8L USM	0.32~0.14	977~1801 (38-7/16~70-15/16)	771~1595 (30-3/8~62-13/16)			
EF300mm f/2.8L USM	0.21~0.09	1899~3786 (74-3/4~149-1/16)	1599~3486 (62-15/16~137-1/4)			
EF300mm f/4L USM	0.24~0.09	1661~3925 (65-3/8~154-1/2)	1385~3649 (54-1/2~143-11/16)			
EF400mm f/2.8L USM	0.19~0.07	2781~6730 (109-1/2~265)	2387~6335 (94~249-7/16)			
EF400mm f/5.6L USM	0.21~0.07	2460~6610 (96-7/8~260-1/4)	2145~6295 (84-7/16~247-13/16)			
EF500mm f/4.5L USM	0.17~0.06	3591~10314 (141-3/8~406-1/16)	3147~9870 (123-7/8~388-9/16)			
EF600mm f/4L USM	0.16~0.05	4413~14214 (173-3/4~559-3/4)	3914~13718 (154-1/16~540-1/16)			
EF1200mm f/5.6L USM	0.13~0.02	11334~53254 (394-1/4~2096-5/8)	9164~52404 (360-13/16~2063-1/8)			
TS-E24mm f/3.5L	1.21~1.10	166~167 (6-1/2~6-9/16)	3~4 (1/8~3/16)			
TS-E45mm f/2.8		Not Available				
TS-E90mm f/2.8	0.60~0.31	373~486 (14-11/16~19-1/8)	207~345 (8-1/8~13-9/16)			

		fication	· ·	stance ranges	Working dist	0
Lens	(X)		mm (inch)			(inch)
	WIDE	TELE	WIDE	TELE	WIDE	TELE
EF20-35mm f/2.8L	Not Available	0.92~0.80	Not Available	181~189	Not Available	28~36
	, tot / trainable	0.52 0.00	TVO( / (Vanatoic	(7-1/8~7-7/16)	NOI AVAIIADIES	(1-1/8~1-7/16)
EF20-35mm f/3.5-4.5 USM	Not Available	1.00~0.80	Not Available	164~176	Not Available	25~37
EF20-33(IIII I/3.3-4.3 U3W	Not Available	1.000.80	NOI Available	(6-7/16~6-15/16)	NOL Available	(1~1-7/16)
EF28-70mm f/2.8L USM	1.050.04	0.64~0.40	213~218	298~374	3~8	112~188
EF28-70(1)(1) 1/2.8L USIVI	1.05~0.94	0.64~0.40	(8-1/4~8-3/8)	(11-7/16~14-9/16)	(1/8~5/16)	(4-7/16~7-3/8)
EEOO OO WAY TO E E CHILICM	1 15- 0.04	0.70- 0.00	164~169	262~417	12~22	107~270
EF28-80mm f/3.5-5.6II USM	1.15~0.94	0.73~0.36	(6-5/16~6-11/16)	(10-1/4~16-9/16)	(1/2~7/8)	(4-3/16~10-5/8)
EEOO AOEssas NO E A E LIGH		0.44.007	177~182	470~630	32~37	298~458
EF28-105mm f/3.5-4.5 USM	0.75~0.73	0.44~0.27	(7~7-3/16)	(18-1/2~24-13/16)	(1-1/4~1-7/16)	(11-3/4~18-7/8)
FFOR OO (4 F OU		070 005	166~181	259~417	26~48	118~283
EF35-80mm f/4-5.6III	0.97~0.75	0.70~0.35	(6-5/8~7-1/8)	(10-3/16~16-7/16)	(1~1-3/8)	(4-11/16~11-3/16)
TEOL OO ULE O HOLL			167~183	253~419	25~48	111~284
EF35-80mm f/4-5.6 USM	0.99~0.75	0.74~0.35	(6-5/8~7-3/8)	(10~16-1/2)	(1~1-3/8).	(4-3/8~11-3/16)
EFOR ADELLA MARIE OLIGIA	0.75 0.70	0.44~0.27	177~183	473~633	40~41	315~476
EF35-105mm f/4.5-5.6 USM	0.75~0.73	0.44~0.27	(7~7-3/16)	(18-5/8~24-15/16)	(1-9/16~1-5/8)	(12-7/16~18-7/8)
FF05 405 (/4 5 01/01)	0.00 0.75	0.47~0.21	181~191	383~917	25~35	201~735
EF35-135mm f/4-5.6USM	0.86~0.75	0.47~0.21	$(7-1/8 \sim 7-1/2)$	(15-1/16~36-1/8)	(1~1-3/8)	(7-15/16~28-15/16)
FFOR OFO NO F F OL LION	0.00 0.75	0.05 0.00	240~250	1490~4953	3~13	1178~4641
EF35-350mm f/3.5-5.6L USM	0.82~0.75	0.25~0.08	(9-1/2~9-7/8)	(58-11/16~194-7/8)	(1/8~1/2)	(46-3/8~182-3/4)
EE70 000 #0 01 HOM	0.44 0.00	0.00 0.14	400~405	956~1728	138~143	694~1466
EF70-200mm f/2.8L USM	0.41~0.38	0.30~0.14	(15-3/4~15-15/16)	(37-5/8~68-1/16)	(5-7/16~5-5/8)	(27-5/16~57-11/16)
EE70 040 4/0 E 4 E 110M	0.47.000	0.05. 0.10	352~398	778~1992	163~210	541~1756
EF70-210mm f/3.5-4.5 USM	0.4/~0.38	0.35~0.13	(13-7/8~15-11/16)	(30-5/8~78-7/16)	(6-7/16~8-1/4)	(21-5/16~69-1/8)
	200 205	0.00 0.00	445~446	1249~3954	239~254	988~3707
EF75-300mm f/4-5.6II USM	0.39~0.35	0.39~0.09	(17-1/2~17-9/16))	(49-3/16~155-11/16)	(9-7/16~10)	(38-7/8~145-15/16)
			451~480	990~1890	299~336	800~1708
EF80-200mm f/4.5-5.6l	0.39~0.33	0.33~0.14	(17-3/4~18-15/16)	(39~74-7/16)	(11-3/4~13-1/4)	(31-1/2~67-1/4)
FF100 000 (/5 0)	0.04 0.07	0.00 0.10	617~660	1264~4013	365~424	984~3749
EF100-300mm f/5.6L	0.34~0.27	0.39~0.10	(24-5/16~26)	(49-3/4~158)	(14-3/8~16-11/16)	(38-3/4~147-5/8)
EE400 000 U4 E E 0 12014	0.07 0.00	0.05 0.00	537~681	1130~4048	347~491	892~3810
EF100-300mm f/4.5-5.6 USM	0.37~0.26	0.35~0.09	(21-1/8~26-13/16)	(44-1/2~17-5/8)	(13-11/16~19-5/16)	(35-1/8~150)

